

SPECIFICATION

Electronic Version 1.2.8

Stylesheet Version 1.0

Finite-Difference Solver Based on Field Programmable Interconnect Devices

Federal Research Statement

The conditions under which this invention was made are such as to entitle the Government of the United States under paragraph I(a) of Executive Order 10096, as represented by the Secretary of the Air Force, to the entire right, title and interest therein, including foreign rights.

Background of Invention

- [0001] The present invention is in the field of analog computation circuits, and in particular relates to the use of the parasitic resistance of field programmable interconnect devices to solve finite difference method problems.
- [0002] The field programmable interconnect device (FPID) is a special-purpose integrated circuit, consisting of a large number of transistor-based electronic switches. The FPID is generically shown in FIG. 1. Its design normally involves a number of externally available input/output (I/O) terminal contacts, a set of wiring pathways, switches between the pathways (represented as circles at a number of the crossing points), and a control circuit that determines which switches are closed based a prescribed pattern, specified from a configuration port. The FPID permits the flexible and agile interconnection between a number of the device's input/output terminals, so that normally isolated parts of a networks can be shorted together, or conversely, so that in designs, some of the connected parts of a network can be isolated by opening switches.
- [0003] In the simplified FIG. 1 representation, each terminal is connected to a row and

column in the wiring array, so that "A" is actually connected to row A and column A, etc. For n terminals, this results in $2n$ wires (n rows and n columns). Though this arrangement results in n^2 junctions of rows and columns, only $(n^2/2 - n)$ switches are required to fully connect the n terminals in any combination. This configuration is sometimes referred to as a fully connected crossbar.

[0004] In the unachievable ideal case, the switches represent zero-ohm, zero-length wires when closed and infinite resistance connections when opened. Since most FPIDs are based on silicon MOSFET devices, however, the switches do not achieve the ideal behavior. FIG. 2 illustrates the various representations of the switch in an FPID. FIG. 2a is the simplified symbolic representation. FIG. 2b is the familiar standard symbolic representation. Figures 2c and 2d represent the n-channel MOSFET and CMOS (n-channel plus p-channel) transmission gate structures respectively, which closely represent the actual switch structures in FPID devices. FIG. 3 provides a more physically accurate representation of an n-channel MOSFET. FIG. 3b illustrates the formation of an inversion channel between the drain and source, resulting in a conductive path, the situation more closely representing the closure of an FPID switch. The switch actually behaves more like a resistor, a fact very important to the principle behind the present invention.

[0005] Since the switch is a poor switch, the FPID is considered a digital device, for use in switched logic systems. Switch logic systems compensate for the slight signal degradations of transmission gates due to the restorative nature of digital logic systems such as CMOS. For general purpose analog, however, the non-zero resistance of the transmission gate switch (values may range from 50 ohms to 500 ohms, based on the underlying switch design and process technology) results in unwanted signal deterioration and design complexity. Hence, even though it is possible to use FPIDs for analog applications, it is uncommon to use them for these applications due to the normally undesired parasitic resistance.

[0006] It is conceivable, however, that the parasitic resistance could be harnessed in particular circuit designs. One such possibility includes the utilization of FPIDs to form certain types of resistive networks, in which the normally parasitic resistance now plays a key role in the operation of that network. One such circuit class is a linear

equation solver, for example, based on the finite difference method.

[0007] The finite difference method uses a discrete approximation of differential equations to reduce them to a system of algebraic equations. For example, the following is a derivation of the finite difference representations of Laplace's equation in one-dimension.

[0008] Define Laplace's equation:

$$\nabla^2 V = 0 \quad (1)$$

[0009]

11
12
13
14
15
16
17
18
19
20
21
22
23
24
25
26
27
28
29
30
31
32
33
34
35
36
37
38
39
40
41
42
43
44
45
46
47
48
49
50
51
52
53
54
55
56
57
58
59
60
61
62
63
64
65
66
67
68
69
70
71
72
73
74
75
76
77
78
79
80
81
82
83
84
85
86
87
88
89
90
91
92
93
94
95
96
97
98
99
100
101
102
103
104
105
106
107
108
109
110
111
112
113
114
115
116
117
118
119
120
121
122
123
124
125
126
127
128
129
130
131
132
133
134
135
136
137
138
139
140
141
142
143
144
145
146
147
148
149
150
151
152
153
154
155
156
157
158
159
160
161
162
163
164
165
166
167
168
169
170
171
172
173
174
175
176
177
178
179
180
181
182
183
184
185
186
187
188
189
190
191
192
193
194
195
196
197
198
199
200
201
202
203
204
205
206
207
208
209
210
211
212
213
214
215
216
217
218
219
220
221
222
223
224
225
226
227
228
229
230
231
232
233
234
235
236
237
238
239
240
241
242
243
244
245
246
247
248
249
250
251
252
253
254
255
256
257
258
259
260
261
262
263
264
265
266
267
268
269
270
271
272
273
274
275
276
277
278
279
280
281
282
283
284
285
286
287
288
289
290
291
292
293
294
295
296
297
298
299
300
301
302
303
304
305
306
307
308
309
310
311
312
313
314
315
316
317
318
319
320
321
322
323
324
325
326
327
328
329
330
331
332
333
334
335
336
337
338
339
340
341
342
343
344
345
346
347
348
349
350
351
352
353
354
355
356
357
358
359
360
361
362
363
364
365
366
367
368
369
370
371
372
373
374
375
376
377
378
379
380
381
382
383
384
385
386
387
388
389
390
391
392
393
394
395
396
397
398
399
400
401
402
403
404
405
406
407
408
409
410
411
412
413
414
415
416
417
418
419
420
421
422
423
424
425
426
427
428
429
430
431
432
433
434
435
436
437
438
439
440
441
442
443
444
445
446
447
448
449
450
451
452
453
454
455
456
457
458
459
460
461
462
463
464
465
466
467
468
469
470
471
472
473
474
475
476
477
478
479
480
481
482
483
484
485
486
487
488
489
490
491
492
493
494
495
496
497
498
499
500
501
502
503
504
505
506
507
508
509
510
511
512
513
514
515
516
517
518
519
520
521
522
523
524
525
526
527
528
529
530
531
532
533
534
535
536
537
538
539
540
541
542
543
544
545
546
547
548
549
550
551
552
553
554
555
556
557
558
559
560
561
562
563
564
565
566
567
568
569
570
571
572
573
574
575
576
577
578
579
580
581
582
583
584
585
586
587
588
589
590
591
592
593
594
595
596
597
598
599
600
601
602
603
604
605
606
607
608
609
610
611
612
613
614
615
616
617
618
619
620
621
622
623
624
625
626
627
628
629
630
631
632
633
634
635
636
637
638
639
640
641
642
643
644
645
646
647
648
649
650
651
652
653
654
655
656
657
658
659
660
661
662
663
664
665
666
667
668
669
670
671
672
673
674
675
676
677
678
679
680
681
682
683
684
685
686
687
688
689
690
691
692
693
694
695
696
697
698
699
700
701
702
703
704
705
706
707
708
709
710
711
712
713
714
715
716
717
718
719
720
721
722
723
724
725
726
727
728
729
730
731
732
733
734
735
736
737
738
739
740
741
742
743
744
745
746
747
748
749
750
751
752
753
754
755
756
757
758
759
760
761
762
763
764
765
766
767
768
769
770
771
772
773
774
775
776
777
778
779
780
781
782
783
784
785
786
787
788
789
790
791
792
793
794
795
796
797
798
799
800
801
802
803
804
805
806
807
808
809
810
811
812
813
814
815
816
817
818
819
820
821
822
823
824
825
826
827
828
829
830
831
832
833
834
835
836
837
838
839
840
841
842
843
844
845
846
847
848
849
850
851
852
853
854
855
856
857
858
859
860
861
862
863
864
865
866
867
868
869
870
871
872
873
874
875
876
877
878
879
880
881
882
883
884
885
886
887
888
889
890
891
892
893
894
895
896
897
898
899
900
901
902
903
904
905
906
907
908
909
910
911
912
913
914
915
916
917
918
919
920
921
922
923
924
925
926
927
928
929
930
931
932
933
934
935
936
937
938
939
940
941
942
943
944
945
946
947
948
949
950
951
952
953
954
955
956
957
958
959
960
961
962
963
964
965
966
967
968
969
970
971
972
973
974
975
976
977
978
979
980
981
982
983
984
985
986
987
988
989
990
991
992
993
994
995
996
997
998
999
1000

In one-dimension, Equation (1) becomes:

$$\frac{d^2V}{dx^2} = 0 \quad (2)$$

The finite forward difference is an approximation of the definition of a derivative:

$$\frac{dV(x)}{dx} \cong \frac{V(x+\Delta) - V(x)}{(x+\Delta) - x} = \frac{V(x+\Delta) - V(x)}{\Delta} \quad (3)$$

Also, define:

$$\frac{dV(x-\Delta)}{dx} \cong \frac{V(x) - V(x-\Delta)}{\Delta} \quad (4)$$

Finite difference representation of higher-level derivatives can be analogously defined:

$$\frac{d^2V(x)}{dx^2} \cong \frac{\frac{dV(x+\Delta)}{dx} - \frac{dV(x)}{dx}}{\Delta} \quad (5)$$

As $\Delta \rightarrow 0$, the approximation improves, being identical to the "true" derivative in the limit as $\Delta \rightarrow 0$. Hence,

$$x \approx (x+\Delta); V(x) \approx V(x+\Delta); \frac{dV(x)}{dx} \approx \frac{dV(x+\Delta)}{dx}; \frac{d^2V(x)}{dx^2} \approx \frac{d^2V(x+\Delta)}{dx^2};$$

etc. So, for convenience we develop the finite difference representation of

$$\frac{d^2V(x-\Delta)}{dx^2}$$

and recognize it as an approximation of

$$\frac{d^2V(x)}{dx^2}$$

using (3) and (4):

$$\frac{d^2V(x-\Delta)}{dx^2} \cong \frac{\frac{dV(x)}{dx} - \frac{dV(x-\Delta)}{dx}}{\Delta} = \frac{\frac{V(x+\Delta) - V(x)}{\Delta} - \frac{V(x) - V(x-\Delta)}{\Delta}}{\Delta}$$

[0010]

$$= \frac{V(x+\Delta) + V(x-\Delta) - 2V(x)}{\Delta^2} \cong \frac{d^2V(x-\Delta)}{dx^2} \cong \frac{d^2V(x)}{dx^2} \quad (6)$$

and therefore we can write a finite difference approximation to (1) (using (6)) as:

$$\begin{aligned} \nabla^2 V &\cong \frac{V(x+\Delta) + V(x-\Delta) - 2V(x)}{\Delta^2} = 0 \Rightarrow V(x+\Delta) + V(x-\Delta) - 2V(x) = 0 \\ &\Rightarrow V(x+\Delta) + V(x-\Delta) = 2V(x) \\ V(x) &= \frac{1}{2}(V(x+\Delta) + V(x-\Delta)) \quad (7) \end{aligned}$$

Equation (7) is then the finite difference representation of Laplace's equation in one-dimension.

To simplify implementation in a discrete system or a computer, the Δ 's are typically replaced by integral indices, yielding the familiar form of a finite difference equation:

$$V(x) = \frac{1}{2}(V(x+i) + V(x-i)) \quad (8)$$

Extending this analysis to multiple dimensions is straightforward. For two dimensions, Equation (1) becomes:

$$\nabla^2 V(x, y) = \frac{\partial^2 V(x, y)}{\partial x^2} + \frac{\partial^2 V(x, y)}{\partial y^2} \quad (9)$$

Through the previous analyses, we can directly write the approximation of Equation (9) as:

$$\begin{aligned} \nabla^2 V(x, y) &\cong \frac{\left(\frac{V(x+\Delta, y) - V(x, y)}{\Delta} - \frac{V(x, y) - V(x-\Delta, y)}{\Delta} \right) + \left(\frac{V(x, y+\Delta) - V(x, y)}{\Delta} - \frac{V(x, y) - V(x, y-\Delta)}{\Delta} \right)}{\Delta} \\ &= \frac{V(x+\Delta, y) + V(x-\Delta, y) + V(x, y+\Delta) + V(x, y-\Delta) - 4V(x, y)}{\Delta^2} = 0 \end{aligned}$$

This results in the two-dimensional finite difference method expression:

$$V(x, y) = \frac{1}{4}(V(x+\Delta, y) + V(x-\Delta, y) + V(x, y+\Delta) + V(x, y-\Delta)) \quad (10)$$

[0011]

Which can be written in the indexed form as:

$$V(x, y) = \frac{1}{4}(V(x+1, y) + V(x-1, y) + V(x, y+1) + V(x, y-1)) \quad (11)$$

In particular, it will be shown that it is possible to reduce the solution of Poisson's equation:

$$\nabla^2 V = \rho$$

over a two-dimensional (2-D) space to an equation at each of many discrete points on a grid formed onto this space:

$$V(x, y) = 1/4 * (V(x+dx, y) + V(x-dx, y) + V(x, y+dy) + V(x, y-dy))$$

An electrical analog of this discretization can then be realized by using a grid network of resistors. Boundary conditions are simulated by impressing voltages on particular nodes. These sources correspond to Dirichlet boundary conditions. Of course, Poisson's equation reduces to Laplace's equation in source-free regions:

$$\nabla^2 V = 0$$

Summary of Invention

[0012] In a preferred embodiment, the invention exploits the parasitic resistances of field programmable interconnect devices in the form of a programmable resistive grid to solve a wide variety of linear partial differential equations. The grid can be programmed to mimic the nodal relationships defined in finite difference method models with voltages impressed on externally accessible pins corresponding to Dirichlet boundary conditions and a means to read out the solutions (voltages) at the grid nodal points. A resistive grid may contain up to hundreds of terminals. Problems requiring even greater nodal points can be solved sequentially using a plurality of resistive grids with the outputs of the first resistive grid component forming the input, boundary conditions of the next resistive grid component. Such an approach has a distinct advantage over custom solvers that are normally higher in performance but fixed in their connection topology.

[0013] Other aspects and advantages of the present invention will become apparent from the following detailed description, taken in conjunction with the accompanying

drawing, illustrating by way of example the principles of the invention.

Brief Description of Drawings

- [0014] FIG. 1 illustrates a generic field programmable interconnect device (FPID).
- [0015] FIG. 2 illustrates various representations of a switch in a FPID, with 2a being a simplified symbolic representation, 2b is the standard symbolic representation, 2c represents the n-channel MOSFET transmission gate structure, and 2d is the n-channel plus p-channel CMOS transmission gate structure.
- [0016] FIG. 3a illustrates an n-channel MOSFET; 3b shows the formation of an inversion channel between the drain (D) and source (S), and 3c illustrates the parasitic resistance of the structure.
- [0017] FIG. 4 is a linear array of connected resistors that is shown to approximate the finite difference representation of Laplace's equation in one dimension.
- [0018] FIG. 5a is a cross-sectional representation of a capacitor.
- [0019] FIG. 5b is a model of the FIG. 5a capacitor as a resistive network.
- [0020] FIG. 6a is a two-dimensional mesh resistor that approximates the finite difference representation of Laplace's equation in two dimensions.
- [0021] FIG. 6b is a north-east-west-south (NEWS) resistor grid pattern of nearest neighbors.
- [0022] FIG. 7a is an electrical analog using a grid network of resistors to represent the solution of Poisson's equation over a 2-D space reduced to discrete points on a grid.
- [0023] FIG. 7b depicts a smaller sub-region of FIG. 7a.
- [0024] FIG. 7c illustrates notionally how switches might be set in a FPID switch array to produce the FIG. 7b sub-region.
- [0025] FIG. 8a illustrates a small sample network in which a number of nodes are forced with a $V=0$ Dirichlet boundary condition and a single node is forced with a $V=1$ Dirichlet boundary condition.

- [0026] FIG. 8b is a table summarizing the required switch closures for the FPID network shown in FIG. 8a.
- [0027] FIG. 9a represents a 2-D confined charge box sample problem with the box shown in cross-section.
- [0028] FIG. 9b is a table of the pin connections and expected measurements for the 9a problem solved by using a FPID device.
- [0029] FIG. 10 illustrates a self-contained FPID with a number of digital-to-analog converters and analog-to-digital converters added to the FPID to produce a hybrid computer.
- [0030] FIG. 11 illustrates temporary connections, made one-at-a-time, to acquire voltage measurements for a FPID.
- [0031] FIG. 12 illustrates a larger network comprised of a plurality of individual FPID's interconnected with reconfigurable terminal pins.
- [0032] FIG. 13 shows a finite difference mesh (11a) that is too large to fit onto one FPID device and 11b shows this mesh might be sectioned into four segments.
- [0033] FIG. 14 shows the solution process for the first complete cycle of a four segment finite difference mesh, where 14a is the first segment corresponding to FIG. 13a, 14b corresponds to 13b, etc.

Detailed Description

- [0034] The purpose of the current invention is to exploit the undesired parasitic resistance in a special class of digital integrated circuits to perform analog computation. This class of integrated circuits, referred to as field programmable interconnect devices (FPID's) act as crossbar switches, permitting the arbitrary connection of many signals attached to the package pins of the components. The invention extends the application of this crossbar to computation, which can now be used as a building block in analog or hybrid (analog plus digital) computer architectures.
- [0035] The present invention exploits the parasitic resistance of FPIDs to form a

programmable resistive grid that can be used to solve certain finite difference method (FDM) problems. A FPID component contains dozens to hundreds of terminals that can be shorted together or isolated under program control. "Shorting" and "isolating" are relative concepts. Since contemporary FPID components are built using MOSFET transistors in silicon integrated circuits configured as switches, their connective paths, formed by path closures, have intrinsic channel resistance. So, instead of "shorting" terminals together, the path closure forms a resistance. This resistance is generally undesirable, but as it is nominally consistent from switch to switch, it is possible to exploit this regularity to form resistive grids. The grids take on configurations as defined by programming the connection paths between any given combination of terminals. Similarly, when the path is opened, an extremely large but finite resistance remains in effect between terminals. Fortunately, for the purposes of the current invention, it is possible to neglect this effect, i.e., to treat the open condition as the ideal case of infinite resistance or isolation.

[0036] Equation 7 was previously shown to be the finite difference representation of Laplace's equation in one dimension. It will now be shown that a linear array of connected resistors implements the approximation of Laplace's equation given in Eq. 7. The network of resistors is defined in FIG. 4. Next, we write equations for $V(x)$ and $V(x + \Delta)$ based on elementary circuit theory:

$$\begin{aligned} V(x) &= V(x - \Delta) + IR \\ V(x + \Delta) &= V(x) + IR \end{aligned}$$

Combining these equations yields Equation (7):

$$V(x + \Delta) = V(x) + (V(x) - V(x - \Delta)) \Rightarrow V(x) = \frac{1}{2}(V(x + \Delta) + V(x - \Delta))$$

The Δ 's are typically replaced by integral indices, yielding the familiar form of a finite difference equation:

$$V(x) = \frac{1}{2}(V(x + i) - V(x - i)) \quad (8)$$

[0037] Consider a very simple 1-D exemplary problem, i.e., solving the electrostatic potential in an infinite slab. In this case, two conducting slabs are provided to contain a dielectric slab, one positioned at $x=0$ and one at $x=1$. Though shown as finite, the slabs are understood to have infinite extent in the y and z axes (an ideal parallel plate capacitor). Boundary conditions are provided in the form of specified voltages at each

conducting slab, namely $V(0)=0$ and $V(1)=1$. This is shown in FIG 5a. The corresponding differential equation problem is simply:

$$\frac{d^2V}{dx^2} = 0$$

with $V(0) = 0$ and $V(1) = 1$.

An analytic solution is quickly developed by integrating this equation, producing

$$\int(0)dx = k_1$$

and once again integrating to produce

$$V(x) = \int k_1 dx = k_1 x + k_2$$

It is obvious that $V(0)=0$ implies that $k_2=0$, and $V(1)=1$ implies that $k_1=1$, producing the very simple result that

$$V(x) = x.$$

$V(x) = x$ becomes a reference verification for a finite difference model representation of the initial problem. Based on the previous discussion, it is straightforward to model the slab as a resistive network.

In this case, the resistances represent discretization of the slab at nine equidistant points as shown in FIG. 5b. The voltage applied to point 1 equals zero volts, whereas the voltage applied to point nine equals one volt. Whether a discrete finite difference model is used in which

$$V_i^{n+1} = \frac{1}{2}(V_{i-1}^n + V_{i+1}^n)$$

[0038] or the resistor network is built and measured or analyzed, clearly the resulting findings will be as follows from points 1 to 9: 0, 0.125, 0.250, 0.375, 0.500, 0.625, 0.750, 0.875, 1,000. This corresponds exactly to the analytic solution previously specified by $V(x) = x$.

[0039] For the two-dimensional (2-D) case, a 2-D mesh resistor (FIG. 6a) implements the finite difference representation for Laplace's equation in 2-D, previously derived in index form as:

$$V(x,y) = \frac{1}{4}(V(x+1,y) + V(x-1,y) + V(x,y+1) + V(x,y-1)) \quad (11)$$

[0040]

As such, a FDM grid can be imposed by establishing a north-east-west-south

(NEWS) pattern of nearest neighbors starting with a chosen terminal (see FIG. 6b) until all the terminals are consumed by the network formed. This resistive network models a Laplacian 2-D partial differential equation. More elaborate, multi-dimensional (when viewed from a Euclidean perspective) grids can easily be established by simply defining the appropriate connective paths.

[0041] The present invention then deliberately exploits the parasitic resistance of FPID's to form a partial differential equation solver. This involves configuring the FPID to create networks similar to that shown in FIG. 7 by closing the appropriate set of switches. By closing FPID switches in this manner, a network of parasitic resistances results. While the parasitic resistance values may vary from one design to another, or even from one lot run to another, the parasitic resistance values across a particular device typically are very closely matched due to process controls used to maximize device yield. Therefore, the FPID can be used as an effective analog-domain equation solver, which can converge much faster than a corresponding digital implementation of the finite difference method.

[0042] FIG. 7a illustrates the resistive grid topology typical of 2-D discretized implementations of a finite difference method equation that can be implemented using the parasitic resistances of switches in a FPID. FIG. 7b depicts a smaller sub-region, and FIG. 7c illustrates notionally how switches might be set in a FPID switch array to produce the FIG. 7b sub-region.

[0043] The implementation of the FPID equation solver is illustrated simply with a small example. FIG. 8a shows a network in which a number of nodes are forced with a $V=0$ Dirichlet boundary condition and a single node is forced with a $V=1$ Dirichlet boundary condition. Two exterior pins are required, a ground pin connected to terminal number 17 for the $V=0$ boundary condition and a connection of a one volt source to terminal number 4 for the $V=1$ boundary condition. No other external connections are required to the FPID, except for the connections required to power the device control circuitry and the configuration port. The pin connections between nodes are then prescribed in an obvious way. For example, pin number 6 is connected to pins number 2, 5, 7, and 10. Any ground connection is achieved by connecting to pin number 17. The table (FIG. 8b) summarizes the required switch closures.

[0044] Once these switch closures have been accomplished, the FIG. 8 network is formed and the solution of Laplace's / Poisson's equation is available very quickly (much less than one microsecond) and can be directly evaluated at any terminal through measurement of the voltage at particular pins. Changing the boundary conditions can be done continuously and independently, without changing the switch configuration. It is also possible to completely alter the network connections, representing a different equation and boundary conditions.

[0045] While the 1-D capacitor case above demonstrates a nearly trivial example, it is equally straightforward to extend the same technique to much more analytically difficult examples. FIG. 9a shows a relatively simple two-dimensional confined charge box. A cross-sectional view of an infinitely long box is shown. An analytic solution of $V(x,y)$ within the box is not easily developed. However, a discretized version can be solved by conventional techniques using a matrix of linear equations or a discrete finite difference numerical method. The problem can also be much more rapidly solved directly using a FPID device. The pin connection and expected measurements are provided in the FIG. 9b table.

[0046] In this case, the pin number corresponds not necessarily to the identically numbered pin on the FPID device, but rather to a specific sequence on sixteen user pins. The voltages on pin #1 and pin #7 (FIG. 9a) are fixed as boundary conditions, and the voltages on other pins are measured after the FPID is suitably programmed to model the neighborhood relationships implied in the shown discretization.

[0047] It is important to indicate that there are practical limits to the use of the FPID as an analog-domain equation solver. First, the excursion range or operational window of an FPID is limited. Therefore the range of voltages impressed upon the FPID must not exceed in a positive or negative polarity the magnitude that would cause the transistor switches in an FPID to breakdown the gate voltage or forward bias the substrate connection, for example. A typical industrial FPID device might permit a voltage range from 0V to 1V for example.

[0048] To simplify and automate the creation and instrumentation of test partial differential equation configurations, it is possible to make a self-contained circuit, such as shown in FIG. 10. Here, a number of digital-to-analog converters (DACs) and

analog-to-digital converters (ADCs) are added to the FPID to produce a hybrid computer. A number of obvious design details are omitted, such as: (1) the bussing arrangements and enable signals for the different peripheral blocks, (2) that the operating windows of the ADC/DAC components must be aligned with the effective operating voltage range of the FPID switch, and (3) the DAC outputs must be themselves isolated (using possibly a transmission gate switch) when they are not used actively in a particular problem formulation. The primary function of the DACs is to inject boundary conditions, while the function of the ADCs is to read analog voltages corresponding to nodal solutions. Therefore, the number of nodal boundary conditions is limited by the number of DAC circuits. The number of ADCs may be as few as one. If the ADC employs an infinite impedance front end, then it is conceivable that an ADC can be tied to a single pin of the FPID. It is then possible, one by one, to close switches between the measurement node (defined as the single pin connected to an analog-to-digital converter) and particular nodes in an active equation under solution for the purposes of measurement. This configuration is suggested in FIG. 11 where temporary connections are made one at a time to acquire voltage measurements. When the input impedance 18 of the ADC is infinite, then the parasitic resistance formed by the temporarily switched measurement connections will not contribute to measurement error. In the case of finite resistance, a systematic (correctable) error due to the corresponding voltage ladder effects.

[0049] It is sufficient, therefore, to obtain all measurements with one ADC per FPID. The addition of more ADCs is only advantageous in the cases where it is necessary to more rapidly acquire signal measurements.

[0050] It is possible to extend these concepts by adding FPIDs. In this case, the external (reconfigurable) terminal pins of FPIDs are interconnected in some way to facilitate the extension of the parasitic networks of the ensemble to a larger effective network. This possibility is suggested in FIG. 12. Two notes are pointed out here. First, the configuration by which the FPIDs are interconnected is shown as a 2-D planar mesh. In fact, an almost arbitrary number of arrangements are possible, including those configurations where pins are shared with more than two FPIDs. Second, the configuration portals of each of the FPIDs are shown as independent. They must be connected to a computer or programming source to supply the commands for switch

closures within the FPIDs. It is possible that, rather than distinct and independent, that the configuration ports might be bussed together or daisy-chain connected together, consistent with the practices used in complex systems containing multiple FPGA devices.

[0051] The primary motivation for using multiple FPIDs is to extend the size of the problem that could be solved using the analog-domain approach that is the basis of the invention. It is also possible to extend the size of solvable problems by extending the FIG. 7 configuration, using a DAC to optionally drive every terminal pin of an FPID. To illustrate how such an approach can be used to solve an "oversized" problem, a simple example is provided in FIG. 13. In this case, a finite difference mesh (FIG. 13a) is too large to fit onto one FPID device. Instead, the problem is sectioned into four pieces or "segments", as suggested in FIG. 13b. The first steps of an iterative solution process are shown in FIG. 14. Briefly, the solution process involves driving the boundaries of the current "segment" with values obtained from simulating the adjacent segments in the last cycle. The DACs are used to force these values temporarily during a given cycle. These values will typically change each cycle, and so they are called floating (Dirichlet) boundary conditions. Initial conditions may be chosen empirically or simply set to null (undriven).

[0052] In FIG. 14, the first complete cycle of a four-segment simulation is shown. The first segment, corresponding to the upper left quadrant of FIG. 13b, is configured or loaded onto the FPID, including any external boundary conditions, which corresponds to FIG. 14a. The FPID is operated very briefly and the boundary cell values are measured and stored. The next piece, corresponding to the upper right quadrant of FIG. 13b, is loaded onto the FPID as suggested in FIG. 14b. In this case, some values from the FIG. 14a simulation, which were measured, are now used themselves as boundary conditions to be driven by the appropriate DACs, providing a more approximate boundary condition set for the new simulation. This new simulation in turn produces node values to be measured and used in subsequent simulations. The process is repeated in FIGURES 14c and 14d, corresponding to the lower left and right quadrants, respectively, of FIG. 13b. In subsequent cycles of the computation process illustrated in FIG. 14, the boundary measurements eventually converge to accurate values for the overall simulation.